

Project Specific Jumper Configuration: LSP PCB W/ MICROPROCESSOR P/N 14996

Jumper Placement & Configurations (CON 9 is @ Bottom of PCB)

Project # _____ - _____ Sales Order # _____ Date ____/____/____

Number of Units with this Configuration _____

NOTES: Setting JP 10 = Right & JP 9 = Right results in no timing operation.

Setting JP 10 = Left & JP 9 = Left results in separate timing for Circuits 1 & 2 based upon setting @ JP 8.

JP #	Function	Project Setting	Options	Description
JP7	Panic Output		NONE Left Right	Standard Output: Output with Panic Mode Active Momentary Output W/ Panic Button Inverted Output with Panic Mode
JP10	Circuit Configuration		NONE Left Right	Output Circuits 1 & 2 operate independently Output CIR 2 if FAN, CIR 1 is standard Output CIR 1 & 2 operate by switch # 1
JP 9	Circuit Timing		NONE Left Right	No Timing CIR 1 & 2 on timer CIR 2 on Timer as FAN
JP 8	Time period on Circuit Timing		NONE Left Right NONE Left Right	If JP9 = Left OR 1 Hr 2 Hr 3 Hrs If JP9 = Right & JP 10=Left (FAN) 15 MIN 0.5 Hr 1 Hr
JP 1	EMS		NONE Right Left	Active OFF (Input signal will turn OFF Output CIR 1 & 2) Active ON (Input signal require for CIR 1 & 2 to operate) Timer JP 6 Require to operate
JP 6	EMS-Timer		NONE Right Left	If JP 1 = NONE or GND (nothing happens) If JP 1 = (+) 8 Hr Timing 10 Hr Timing 12 Hr Timing
JP2	EMS Input		1 Jumper @ Center 2 Jumpers	24-vac Input Dry-contact Input
JP5	ALARM Input		1 Jumper @ Center 2 Jumpers	24-vac Input Dry-contact Input
JP4	Panic/Alarm Input		Jumper @ Lower Jumper @ Upper	Remote Panic places unit into Alarm State Remote Panic places unit into Panic State
JP3	Panic Output		1 Jumper @ Center 2 Jumpers	Dry-contact Output 24-vac Output

DOC# 14038

August 2015

ISIMET/MAPA, LLC
(903) 897-0737

103 W. CJ Wise Parkway
toll free (866) 897-0737
www.ISIMET.com

Naples, TX 7556
Fax (903) 897-0740